

# TechnoParts

Electronic Parts & Electro Technical Equipment

## AMP-VOLT-METER

## 100-300VAC50A



100 to 300 Volt & 0 to 50 Ampere Panel Meter

With Blue LCD Backlight

### Feature:

Convenient to use  
Don't need additional power supply or AC-DC transformer  
The Panel Meter displays voltage and current at the same time

### Specification:

Working voltage: AC 100V~300V , Volt Accuracy : 1V  
Alternating current: 0~50A , Current Accuracy : 0.1A  
Power Consumption: <0.2VA  
Working temperature : -10°C to +50°C  
Operating Humidity: 10% to 80% (non-condensing)  
Viewing Area: 48 x24.5mm  
Size : 70 x 39 x 40mm  
Mounting cutout: 68 x 38mm

